# HI-SPEED USB 2.0 SATA 3.5" EXTERNAL ENCLOSURE

# USER MANUAL

MODEL 702959

MANHATTAN

BRINGING COMPUTERS TO LIFE

MAN-702959-UM-0706-01

Congratulations on purchasing the MANHATTAN® Hi-Speed USB 2.0 SATA 3.5" External Enclosure, Model 702959. This device will let you quickly and easily transfer, share and archive data, and expand storage capacities for desktop and notebook PCs. Among the main features:

- Supports Hi-Speed USB 2.0 data transfer rates of up to 480 Mbps and SATA up to 3 Gbps
- Lightweight, compact design for increased portability
- Sturdy aluminum case protects drive and facilitates cooling
- Fits standard 3.5" SATA drives with easy, quick installation
- Windows and Macintosh compatible, Plug and Play, hot swappable
- Lifetime Warranty

Package contents:

- External Enclosure with CD Driver and Stand
- USB A-type male to B-type male cable, 4 ft. (1.2 m)
- SATA I-type to I-type flat cable, 5 ft. (1.5 m); SATA I-type to L-type bracket (fits regular PC slots)
- AC power adapter with cable, 9 ft. (2.7 m)
- User Manual

## SETTING UP THE EXTERNAL ENCLOSURE

*NOTE:* Before connecting the SATA drive, set it to Master mode, if applicable. Also, create a copy of your original data to prevent the possibility of data loss should a mistake be made during setup. MANHATTAN accepts no responsibility for lost data.

1. Remove the tray from the enclosure.

2. Connect the SATA and power cables to the disk drive and screw in place.



3. Insert your hard disk drive into the enclosure.

4. Attach the back cover with the 4 screws to complete the procedure.

USB 2.0 Windows 98SE Installation: Place the installation CD in the CD-ROM and connect the external enclosure to your computer. Auto Detect will run the Add New Hardware wizard, which searches for Jmicron: SATA-USB Combo Device. Click "Next."

Select "Search for the best driver for your device (recommended)"; click "Next."

Select "Specify location"; browse to "CD-ROM:\Win98 Driver Jm20336"; click "Next." With the prompt "Windows driver file is now searching for the Jmicron: SATA-USB Combo Device," click "Next." Restart your computer to complete the installation.

*NOTE:* For Windows Me/2000/XP, no need to install the additional driver: It's already installed. Windows XP needs to be updated with SP2.

SATA Installation: There is no need for drive setup: The interface is already installed. Use it to boot your operating system, or use Plug and Play. *NOTE:* Don't hot swap when using the boot-up function. You can also use the SATA I-type to L-type bracket for direct computer connection.

MANHATTAN

**www.manhattan-products.com**

Are you completely satisfied with this product?
Please contact your MANHATTAN® dealer with comments or questions.

Copyright © MANHATTAN
All products mentioned are trademarks or registered trademarks of their respective owners.